

# Platform Install Guide

1 of 2

---

- Step 1  
Right click on Platform Install exe file – Left click on Run as administrator  
- XP users can just double left click
- Step 2  
When program launches – Choose Next to start install – Cancel to exit
- Step 3  
Keep install folder the same unless you need to install in different location.  
- Click Next
- Step 4  
For install Type – Select Simple – Click Next
- Step 5  
Keep Center Port and Database Port at default settings – 8000 and 3306  
- Click Next
- Step 6  
If you do not want Program Icons on your desktop uncheck –create a desktop icon  
- Otherwise Click Next
- Step 7  
At Ready to install screen – Click Install
- Step 8  
Once install is completed click Finish
- 

## Quick Configure Program Settings

- Step 1  
Double left click on Config Client
- Step 2  
At login screen enter in the following:  
User Id – admin  
Password – 123456  
Server – localhost  
Media Port – 8000
- Step 3  
Place check mark in Remember me if desired  
Login
- Step 4  
In main Config program left click on Add Device

Step 5

Enter in your information for your DVR / NVR

Device Name – can be anything

Device Description – can be anything

Device Type – DVR/NVR/IPC

Device Address – enter in your IP or DDNS information

Device Port – 8108 is default control port for DVR / NVR

Login User – This ID must match what's in the device

Login Password – This password must match user's login

- Click OK to save and connect

Step 6

Once connection status turns to 'Online' you can exit the Config program

Step 7

Open Monitor Client

Step 8

If you did not select "Remember me" you must enter in your ID and PW

User ID – admin

Password – 123456

- Click Login

Step 9

When Monitor Client opens – Left click on Config

Step 10

In Config screen – Click on Preview tab on left side

Step 11

Select network stream

Step 12

Next click on General tab on left

- Click Apply

Step 13

Click on Preview

- In device list left click and hold to drag device name to camera position one

Step 14

After cameras all load for the first time. Exit the program and re-launch the Monitor Client to verify your settings

For more information on the Monitor Client program please refer to your user manual.